



5BK7-A

**5BK7-A
TO
5BR8**

MEDIUM-MU TWIN TRIODE

9-PIN MINIATURE TYPE

For use in direct-coupled cathode-drive circuits of TV tuners in equipment having series heater-string arrangement

The 5BK7-A is the same as the 6BK7-B except for the following items:

Heater, for Unipotential Cathodes:

| | | |
|------------------|-----|--------------------------|
| Voltage. | 4.7 | ac or dc volts |
| Current. | 0.6 | amp |

5BQ7-A

MEDIUM-MU TWIN TRIODE

LOW-NOISE 9-PIN MINIATURE TYPE

For use in direct-coupled cathode-drive circuits of TV tuners in equipment having series heater-string arrangement

The 5BQ7-A is the same as the 6BQ7-A except for the following items:

Heater, for Unipotential Cathodes:

| | | |
|----------------------------------|------|--------------------------|
| Voltage. | 5.6 | ac or dc volts |
| Current. | 0.45 | amp |
| Warm-up time (Average)*. | 11 | sec |

5BR8

MEDIUM-MU TRIODE— SHARP-CUTOFF PENTODE

9-PIN MINIATURE TYPE

Intended for use in equipment having series heater-string arrangement

The 5BR8 is the same as the 6BR8 except for the following items:

Heater, for Unipotential Cathodes:

| | | |
|----------------------------------|-----|--------------------------|
| Voltage. | 4.7 | ac or dc volts |
| Current. | 0.6 | amp |
| Warm-up time (Average)*. | 11 | sec |

* For definition of heater warm-up time and method of determining it, see sheet HEATER WARM-UP TIME MEASUREMENT at front of this Section.